

OPTICAL SIGNAL GENERATOR WITH STABILIZED
CARRIER FREQUENCY OUTPUT

5 CROSS-REFERENCES TO RELATED APPLICATIONS

This application claims the benefit of United States Provisional Application No. 60/294,919 to Graves et al., filed on June 1, 2001.

10

FIELD OF THE INVENTION

The present invention relates generally to optical communications networks and, more particularly, to techniques for controlling the frequency of optical carrier signals used in such networks.

BACKGROUND OF THE INVENTION

20 In a modern optical communications network, multiple optical carriers transport digital traffic between access multiplexers at the edges of the network and photonic switch nodes located at strategic points within the core of the network. The link between a particular access
25 multiplexer and a particular photonic switch node may be adapted to run only one wavelength per fiber or it may adhere to a multi-wavelength carrier frequency plan with typically 400-500 GHz spacing (referred to as "Sparse DWDM" since, although the individual optical carriers are
30 generated with the required stability for DWDM transmission, they are widely spaced to create a known sparse population of the DWDM grid). Despite the low concentration of optical carriers on a given link,

however, each modulated optical carrier transmitted by the access multiplexer has to appear at a precisely controlled optical frequency. This is because upon receipt at the photonic switch node, signals may be
5 multiplexed together by a process of interleaving into a true DWDM stream for transmission through the core DWDM trunking network to other access multiplexers or to a core node router without undergoing any wavelength conversion.

10

The set of acceptable wavelengths for the optical carriers is known as the interoffice trunking wavelength plan, which has a narrower grid in order to achieve the large payload capacity of a high number of optical
15 carriers on each fiber. This spacing is generally on the order of 100-200 GHz or less, and 100 GHz will be assumed here for simplicity. To facilitate interoperability, interoffice trunking wavelength plans are typically specified by the International Telecommunications Union
20 (ITU). In order for a modulated optical carrier to be transmittable from one access multiplexer directly across a DWDM network to another access multiplexer or core node router without undergoing wavelength conversion, the optical carrier has to be precise to a small part of the
25 DWDM grid, possibly to within at +/- 1-3 GHz for a 100 GHz grid, and even tighter tolerances for a closer optical grid spacing.

A conventional approach to providing precisely controlled
30 optical signal sources would consist of placing very precise and necessarily tunable optical sources at each access multiplexer. However, this is not only expensive,

14041ROUS01U

but is especially difficult to implement due to the location of the access multiplexers and their isolation from any reference, requiring it to make use of a self-contained and necessarily tunable or provisionable high
5 precision source. Thus, the solution is in this case expensive and unreliable, as the number of sources scattered throughout the network is very large and thus the probability of a malfunction or mis-programming of a remoted function is higher.

10

If, on the other hand, unmodulated optical carriers were distributed to the access multiplexer from a centralized source, only to be turned around and modulated before being sent to the photonic switching node, then it is
15 conceivable that all the necessary optical carriers could be generated at a single location under tightly controlled conditions and assembled into the necessary groups for distribution in specific appropriate groups to match access architectures, modularities, optical carrier
20 plans, etc. This would permit the generation of optical wavelengths that are sufficiently precise in optical frequency such that optical carriers received at the photonic switch nodes could be directly coupled into the interoffice trunking wavelength plan, as required.

25

Thus, in a photonic switch node hosting, for example, 500 access-side optical carrier ports, each potentially associated with an access multiplexer, and utilizing a 5 phase, 8 channel sparse-DWDM plan mapping over a 40-
30 channel interoffice trunking wavelength plan, 40 centrally located optical sources with appropriate buffering, amplification and splitting could do the work

of 500 tunable sources further out in the access multiplexers. Furthermore, the technical requirements for locking 40 devices would be far less complex and far less costly than those for an individual tunable optical carrier locking system at each access multiplexer. Clearly, therefore, economies of scale can be achieved by distributing the wavelengths from a central point. In addition, the wavelengths could be generated in a benign environment and could be readily locked to grid, including locked to any reference wavelength distributed as a network master reference.

SUMMARY OF THE INVENTION

According a broad aspect, the invention provides an apparatus for stabilizing an optical carrier frequency of a generated carrier signal with respect to a target carrier frequency. The apparatus includes a multi-channel optical filter for filtering the generated carrier signal, thereby to provide a first filtered optical signal and a second filtered optical signal, each filtered optical signal including the portion of the generated carrier signal contained in a pass band surrounding a respective channel center frequency. The apparatus also includes a detection unit for determining an indication of a characteristic of the target carrier frequency in the first and second filtered optical signals, as well as a control unit for adjusting the optical carrier frequency of the generated carrier signal as a function of the difference in the indication of the characteristic of the target carrier frequency in the first and second filtered optical signals.

According to another broad aspect, the invention provides an optical signal generator, including an optical source adapted to generate an optical signal containing at least one carrier signal at a respective generated carrier frequency that is adjustable by a corresponding frequency control signal, each carrier signal being associated with a respective target carrier frequency. The optical signal generator also includes a multi-channel optical filter having a filter input port connected to the optical source and having a plurality of filter output ports, each filter output port being associated with a respective optical channel having a pass band surrounding a respective channel center frequency.

The optical signal generator also includes, for at least one target carrier frequency, a first and a second detection unit each associated with the target carrier frequency and connected to different ones of the filter output ports, each detection unit associated with a particular target carrier frequency being adapted to output an indication of a characteristic of the particular target carrier frequency in the optical signal present at the filter output port to which the detection unit is connected.

The optical signal generator further includes a control unit connected to the detection units and to the optical source, the control unit being operable to generate the frequency control signal corresponding to a particular carrier signal as a function of the output of the detection units associated with the target carrier

frequency associated with the particular carrier signal, thereby to align the generated carrier frequency of the particular carrier signal with the target carrier frequency associated with the particular carrier signal.

5

The invention may be summarized according to yet another broad aspect as a method of stabilizing an optical carrier frequency of a generated carrier signal with respect to a target carrier frequency. The method includes filtering the generated carrier signal to provide a first filtered optical signal and a second filtered optical signal, each filtered optical signal including the portion of the generated carrier signal contained in a pass band surrounding a respective channel center frequency. The method also includes determining an indication of a characteristic of the target carrier frequency in the first and second filtered optical signals. The method further includes adjusting the optical carrier frequency of the generated carrier signal as a function of the difference in the indication of the characteristic of the target carrier frequency in the first and second filtered optical signals.

The invention may also be summarized broadly as a computer readable storage medium containing a program element for execution by a computing device to implement the above method.

According to still another broad aspect, the invention may be summarized as an apparatus for stabilizing an optical carrier frequency of a generated carrier signal with respect to a target carrier frequency. The

apparatus includes a detection module adapted to receive a first filtered optical signal and a second filtered optical signal, each filtered optical signal including the portion of the generated carrier signal contained in a pass band surrounding a respective channel center frequency, the detection module further adapted to determine an indication of a characteristic of the target carrier frequency in the first and second filtered optical signals. The apparatus also includes a control module for adjusting the optical carrier frequency of the generated carrier signal as a function of the difference in the indication of a characteristic of the target carrier frequency in the first and second filtered optical signals.

These and other aspects and features of the present invention will now become apparent to those of ordinary skill in the art upon review of the following description of specific embodiments of the invention in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

In the accompanying drawings:

- Fig. 1 shows in schematic form part of a communications network utilizing a multi-carrier optical signal source in accordance with the present invention;
- Fig. 2A shows in schematic form a multi-carrier optical signal source in accordance with a first embodiment of

the present invention, producing a single full spectrum DWDM optical carrier "comb" output;

Fig. 2B shows in schematic form a multi-carrier optical
5 signal source in accordance with a variant of the first embodiment of the present invention, producing a full complement of S-DWDM optical carrier "comb" outputs in complete S-DWDM groups;

10 Figs. 3A and 3B illustrate example individual channel responses for part of the overall response of two example wavelength division demultiplexing devices suitable for use with the multi-carrier optical signal source of Fig. 2A and the positions of various optical carrier spectral
15 lines within their passbands when the multi-carrier optical signal source is stabilized;

Fig. 4 shows in schematic form a multi-carrier optical
signal source in accordance with a second embodiment of
20 the present invention;

Fig. 5 illustrates example individual channel responses for part of the overall response of a wavelength division demultiplexing device suitable for use with the multi-
25 carrier optical signal source of Fig. 4 and the positions of various optical carrier spectral lines within their passbands when the multi-carrier optical signal source is stabilized;

30 Fig. 6 shows in schematic form a multi-carrier optical signal source in accordance with a third embodiment of the present invention;

Fig. 7 illustrates example individual channel responses for part of the overall responses of a wavelength division demultiplexing device suitable for use with the multi-carrier optical signal source of Fig. 6 and the positions of various optical carrier spectral lines within their passbands when the multi-carrier optical signal source is stabilized;

Fig. 8 shows in schematic form a multi-carrier optical signal source in accordance with a fourth embodiment of the present invention;

Fig. 9 shows in schematic form a multi-carrier optical signal source in accordance with a fifth embodiment of the present invention;

Fig. 10 illustrates example individual channel responses for part of the overall response of a wavelength division demultiplexing device suitable for use with the multi-carrier optical signal source of Fig. 9;

Fig. 11 shows in schematic form a multi-carrier optical signal source in accordance with a sixth embodiment of the present invention;

Fig. 12 shows in schematic form a multi-carrier optical signal source in accordance with a seventh embodiment of the present invention;

Fig. 13 shows in schematic form a multi-carrier optical signal source in accordance with an eighth embodiment of the present invention; and

- 5 Fig. 14 shows in schematic form a multi-carrier optical signal source in accordance with a ninth embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

10

- Fig. 1 shows part of a network in which access multiplexers 110 communicate with a photonic switch node 120 over an optical medium such as optical fiber. Individual optical carriers are used to transport modulated data from the access multiplexers 110 to the photonic switch node 120 (i.e., in the "edge-to-core" direction) and from the photonic switch node 120 to the access multiplexers 110 (i.e., in the "core-to-edge" direction), as well as across the core network (via intermediate photonic switches) to far end equipment such as remotely located access multiplexers.

- In one example embodiment, a total of $N = 40$ optical carriers on the standard ITU 100 GHz grid may be used in the core network. This may be extended into the access portion of the network or, alternatively, the total capacity of the core DWDM grid may be shared over multiple access fibers, each carrying a lesser number of optical carriers (referred to as "sparse" DWDM or S-DWDM). In a network of this form, utilizing direct optical (i.e., photonic) switching at the transmitted optical carrier wavelengths, the optical carriers must

always be at a precise enough optical frequency that their spectral lines and modulation sidebands fall within the respective ITU DWDM grid tolerances.

- 5 The optical carriers used to transport modulated data in the edge-to-core direction are transmitted in unmodulated form from the photonic switch node 120 to the access multiplexers 110 so that they can be modulated with data by the access multiplexers 110 and sent back towards the
- 10 photonic switch node 120. In order to prevent these unmodulated optical carriers from overwriting modulated optical carriers travelling to the access multiplexers 110 at the same time, an access S-DWDM frequency plan may be used which establishes specific relationships between
- 15 wavelength allocation in both directions of communication. The simplest of these is that every core-to-edge modulated optical carrier that carries an odd channel number on the ITU grid is associated with the next higher even numbered wavelength for the edge-to-core path and that every even numbered core-to-edge wavelength
- 20 is associated with the next lower odd edge-to-core wavelength. This ensures full use of a bi-directional DWDM core network, with no wavelength wastage, while preventing overwriting of the edge-to-core data stream with the unmodulated optical carrier used to generate the
- 25 associated edge-to-core optical carrier.

More generally, a set of G wavelength groups WG_1, WG_2, \dots, WG_G may be defined. In one embodiment, group WG_g may

30 include optical carriers $g + (k \times N/G)$, for $0 \leq g \leq G-1$. Thus, where $N = 40$ and $G = 8$, group WG_1 would include optical carriers 1, 6, 11, 16, 21, 26, 31 and 36, group

WG₂ would include optical carriers 2, 7, 12, 17, 22, 27, 32 and 37, and so on. For a given access multiplexer 110, different wavelength groups are used for transporting modulated data in the two directions of transmission. In this way, unmodulated optical carriers which are part of the access multiplexer's edge-to-core wavelength group will not interfere with the modulated optical carriers travelling simultaneously towards the access multiplexer 110.

The same applies to other access multiplexers 110 in the network and thus it should be appreciated by those skilled in the art that the photonic switching node 120, as part of its functionality, effectively acts as a central distribution hub for unmodulated optical carriers to the access multiplexers 110. These optical carriers can be coupled in to the access path by action of the switch core, though this can be wasteful of switch ports, or they can be coupled in at the output point of the downstream portion of an access port card, either by consuming ports on the downstream S-DWDM multiplexers (turning them from 5 phases of 8 channels into five phases of 8+8 channels) or the optical carriers can be generated in the multi-lambda source as five groups of 8 channels of optical carriers, which are then distributed to each and every port card for coupling into the downstream access output beyond the S-DWDM multiplexer.

In any event, the unmodulated optical carriers must be generated at precisely controlled wavelengths so that (a) in unmodulated form, they do not interfere with modulated optical carriers as they are sent to the access

5 multiplexers 110, (b) upon modulation by the access multiplexers 110, they do not interfere with modulated optical carriers from other wavelength groups as they are switched by the photonic switch node 120, and (c) the entire modulated signal on each optical carrier (including upper and lower sidebands) falls within the passband of the wavelength division multiplexing and demultiplexing equipment.

10 In order to permit the generation of the required number of unmodulated optical carriers at precisely controlled wavelengths, the photonic switching node 120 comprises or is coupled to a multi-carrier optical signal source 100. In one example embodiment, the multi-carrier optical
15 signal source 100 generates $N = 40$ optical carriers on the standard ITU 100 GHz grid. However, it is within the scope of the present invention to generate other numbers of optical carriers in accordance with any suitable spectral plan. It should further be understood that the
20 present invention is also applicable to the stable generation of a single optical carrier.

The optical carriers generated by the multi-carrier optical signal source 100 are grouped or multiplexed by a
25 set of multiplexers 105 in accordance with a wavelength plan. If interleaving of optical carriers is required, this functionality may be supplied by a coupler or interleaver device (not shown). A resulting group of optical carriers may then fed through an amplifier /
30 splitter combination 130, which may be built from discrete components or may comprise an amplifying

splitter such as an amplifying 8-way splitter available from TEEM Photonics, Grenoble, France.

5 The purpose of the amplifier / splitter combination 130, if used, is to allow the optical carriers in the corresponding group to be sent towards different access multiplexers 110 in different parts of the network. This permits re-use of the wavelength plan within the network. The splitter may be omitted, in which case the amplifier
10 / splitter combination 130 may simply include an amplifier with a flat gain / frequency response.

15 Different embodiments of the multi-carrier optical signal source 100 are described herein below with reference to Figs. 2-14. Fig. 2A shows a first embodiment of the multi-carrier optical signal source of the present invention, comprising a plurality of lasers L_i , each associated with a respective optical carrier i and a system frequency F^*_i , where i ranges from 1 to N . The N
20 required system frequencies F^*_i are laid out in accordance with a specific optical frequency plan. A non-limiting example of a possible optical frequency plan consists of $N = 40$ optical carriers with system frequencies evenly spaced apart by 100 GHz, thereby
25 forming a grid, suitably an ITU-specified grid.

Laser L_i lases at a controllable carrier frequency $F_i = F_i^{\text{open}} + \Delta F_i$ and at a controllable carrier amplitude (intensity) $A_i = A_i^{\text{nom}} + \Delta A_i$, where F_i^{open} is the open
30 loop frequency of laser L_i in the absence of feedback control and A_i^{nom} is the amplitude resulting from the

application of a predetermined bias current (also known as "drive current") to laser L_i .

5 The open loop frequency F_i^{open} is approximately equal to a corresponding one of the required system frequencies F_i^* . However, due to various factors, the open loop frequency F_i^{open} may deviate from the corresponding required system frequency F_i^* ; still, F_i^{open} is always assumed to remain in the "neighbourhood" of F_i^* . As an
10 example of an implementation to support this assumption, a Fabry-Perot laser with an integrated Bragg fiber grating in series therewith is known to have a free-running frequency stability of ± 18 GHz, thereby resulting in a free grid spacing ranging over 64-136 GHz,
15 against an objective of a spacing of substantially 100 GHz. Nevertheless, in the event that the "neighbourhood" assumption is not satisfied, the present invention contemplates other embodiments, which are described later on in greater detail.

20 To lock the carrier frequency F_i to the corresponding required system frequency F_i^* , the present invention as embodied in Fig. 2A (or Fig. 2B) provides a frequency control feedback loop for each laser L_i under the control
25 of a respective laser controller C_i . The frequency control loop utilizes an array waveguide (AWG) dense wavelength division demultiplexer (WDD) 228 with a precisely known amplitude vs. frequency response in each passband lobe, including side lobes, in order to provide
30 precise conversion from optical frequency to amplitude slope.

The frequency control loop involves laser controller C_i generating a frequency adjustment signal ΔF_i by evaluating the difference in amplitude of two signals derived from side lobe responses of the WDD 228, which
5 interact to operate as frequency discriminator. To this end, and as will be described in further detail later on, an (electrical) tone frequency T_i is associated with optical carrier i , $1 \leq i \leq N$. The tones are used to discriminate the contributions from each of a plurality
10 (e.g., three) of optical carriers in each passband of the WDD device 228. In one embodiment, for the i^{th} passband of the WDD device 228, a relatively strong contribution from optical carrier i will be received in the center of the passband, whereas a relatively weak contribution from
15 optical carrier $i-1$ will be received at the lower edge of the passband and another relatively weak contribution from optical carrier $i+1$ will be received at the upper edge of the passband.

20 As will be described in greater detail later on, all three contributions (from optical carriers $i-1$, i and $i+1$) arrive at a common opto-electronic receiver, and thus the relative contributions of the three optical carriers cannot be distinguished using d.c. or power
25 measurement techniques alone. However, by associating each optical carrier with a tone, there will appear three tones T_{i-1} , T_i , T_{i+1} of differing powers, representing optical carriers $i-1$, i and $i+1$, respectively. The method for discriminating the actual operating frequency
30 of laser L_i , associated with optical carrier i , includes measuring the power of tone T_i in lobe $i-1$ and the power of tone T_i in lobe $i+1$ and comparing the received power

of these two tone signals. This results in a measured amplitude offset, denoted AO_i , which is then compared to a design-dependent offset AO^*_i associated with optical carrier i . In one embodiment, the design-dependent
5 offset AO_i^* is zero and the discriminator is said to be balanced when optical carrier i sits at a carrier frequency F_i such that exactly equal signal levels are measured in the two adjacent side lobes.

10 The frequency adjustment signal ΔF_i feeds suitable circuitry within laser L_i for shifting F_i^{open} by ΔF_i , thereby creating F_i . Such circuitry is known in the art and may include a third electrode for applying a voltage or current to laser L_i so as to operate upon either the
15 lasing channel parameters in order to shift the frequency F_i , or upon a heater/cooler in order to change the thermal equilibrium of laser L_i , thus exploiting its temperature coefficient of optical lasing frequency. In other embodiments, such circuitry may act directly upon
20 the drive current through laser L_i . The method used will be dependent on the device construction and on the operational requirements of the invention.

To maintain the carrier amplitude A_i at a desired level,
25 the present invention as embodied in Fig. 2A (or Fig. 2B) provides an amplitude control loop for each laser L_i under the control of a respective laser controller C_i . The amplitude control loop involves laser controller C_i generating an amplitude adjustment signal ΔA_i from a
30 respective measured carrier amplitude AV_i , from a desired carrier amplitude AV^*_i and from a low-level modulation

signal at an (electrical) tone frequency T_i associated with optical carrier i .

The amplitude adjustment signal ΔA_i generated by laser controller C_i contains a d.c. component (which is a function of the measured carrier amplitude AV_i and the desired carrier amplitude AV^*_i) and an a.c. component (at the tone frequency T_i). The amplitude adjustment signal ΔA_i is fed to suitable circuitry within laser L_i for adding ΔA_i to A_i^{nom} , thereby to create A_i . By way of a non-limiting example, the modulation depth, defined as the magnitude of ΔA_i relative to d.c. component of A_i , can range from 0.2 to 2 %. However, it should be understood that any modulation depth could be used which does not cause a substantial increase in laser line width or reduction in high-speed receiver eye opening, and which also results in an adequate discrimination sensitivity in the frequency control loop.

By way of example, later described with reference to Fig. 13, alternative instantiations can exist where laser L_i is not itself power modulated with tone T_i , but rather its output is tapped by a 95%/5% splitter. The 5% leg of the splitter is provided with a series tone modulator. The set of modulated tapped components are combined together via a passive splitter or broad-lobe WDM device, to create an input to the WDD device 228. While slightly more complex, this approach has the advantages that (i) no tone or line width broadening due to the tone is present at the 95% leg of the splitter; (ii) the output modularity or granularity, in terms of whether the output is individual optical signals, S-DWDM multiplexed sparse

combs or a dense comb for DWDM is independent of the control loop components; and (iii) the constraints on the level of modulation of tone T_i are relaxed, allowing greater modulation depth and hence better discriminator
5 sensitivity.

Each laser thus outputs a single-carrier optical signal which is fed to a common wavelength division multiplexing (WDM) device 222. The WDM device 222 combines the N
10 single-carrier optical signals into a composite, multi-carrier optical signal. The output of the WDM device 222 is connected, via a splitter 224, both to the core network 226 and to the WDD device 228, which has specific properties dependent upon the detailed design of the
15 locking control system of which several embodiments will be described herein below. The splitter 224 may suitably divert between 5 and 10 % of the optical power of the multi-carrier optical signal towards the WDD device 228, while feeding the rest of the power to the core network
20 226. Of course, those skilled in the art will appreciate that other power splitting ratios are possible.

In an alternative embodiment, as shown in Fig. 2B, if the optical carriers are to be assembled into groups of
25 optical carriers by a plurality of smaller multiplexers (instead of a into a single multi-carrier optical signal by the WDM device 222), then splitters similar to splitter 224 could be located at the outputs of these smaller multiplexers and could feed a combiner (or
30 multiplexer) which would then feed the WDD device 228.

The WDD device 228 is substantially a multi-channel optical filter with precisely known response characteristics. In the embodiment of Fig. 2, the WDD device 228 has $N+2$ output ports P_i , $0 \leq i \leq N+1$, one for each of $N+2$ optical channels of width 100 GHz. Each port is associated with an optical channel having an optical pass band centered about a unique channel center frequency $F_{ch,i}$. In the specific embodiment of Fig. 2, the channel center frequencies $F_{ch,i}$ (which are associated with the N middle ports P_i , $1 \leq i \leq N$) correspond to system frequencies F^*_i . The two other ports of the WDD device 228, namely P_0 and P_{N+1} , are associated with optical channels centered about frequencies $F^*_1 - 100$ GHz and $F^*_N + 100$ GHz, respectively. The usefulness of ports P_0 and P_{N+1} will become apparent from the discussion herein below.

Advantageously, the passband lobes of the WDM device 222 may be chosen to be significantly wider than the passband lobes of the WDD device 228, so that the WDD device 228 will dominate the discrimination process, since the two components' responses are additive. A suitable WDM device 222 is a FATMux part from Lightwave Microsystems.

Fig. 3A shows, by way of a non-limiting example, the response of three adjacent optical channels, corresponding to ports P_8 , P_9 and P_{10} of the WDD device 228 and centered about frequencies $F_{ch,8}$, $F_{ch,9}$ and $F_{ch,10}$. For the WDD device 228 in the embodiment of Fig. 2, channel center frequencies $F_{ch,8}$, $F_{ch,9}$ and $F_{ch,10}$ would correspond to system frequencies F^*_8 , F^*_9 and F^*_{10} , respectively. It is seen that the response of each

optical channel overlaps the other and has a shape consisting primarily of a main lobe and symmetrically disposed side lobes. Each side lobe is located at a distance away from the main lobe such that the response
5 has opposite slopes when measured at the center frequencies of the two adjacent optical channels. Each of the remaining optical channels (not shown) has a similarly shaped response, but would be shifted by 100 GHz so that it would be centered about the appropriate
10 system frequency F^*_i associated with optical carrier i .

Of course, it should be understood that different WDD devices can be used and will lead to different embodiments of the invention, depending on the inter-
15 channel spacing, on the shape of each individual channel response and on variations in the response shape among optical channels. Specific embodiments of the present invention illustrating some of these possibilities are provided later on.

20 Continuing with the description of Fig. 2, each output port P_i ($0 \leq i \leq N+1$) of the WDD device 228 is connected to a respective low-bandwidth optical receiver, denoted R_i for $0 \leq i \leq N+1$, which is adapted to provide opto-
25 electronic conversion functionality. Each of the "middle" optical receivers (i.e., those receivers R_i for which $1 \leq i \leq N$) outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal which falls in the passband of port P_i on the WDD
30 device 228, centered about the corresponding channel center frequency $F_{ch,i}$ which, in the embodiment of Fig. 2, corresponds to system frequency F^*_i . Receivers R_0 and

R_{N+1} output a low-bandwidth version of the portion of the multi-carrier optical signal centered about $F^*_1 - 100$ GHz and $F^*_N + 100$ GHz, respectively.

- 5 The portion of the multi-carrier optical signal centered about channel center frequency $F_{ch,i}$ will contain the optical carrier at carrier frequency F_i (which is to be locked to the corresponding system frequency F^*_i), a controlled component from each of the adjacent optical
- 10 carriers at around $F_i + 100$ GHz and $F_i - 100$ GHz (which are to be used in conjunction with the controlled components received in other lobes to provide a frequency locking mechanism), as well as residual noise or breakthrough components from other more distant optical
- 15 carriers, depending on the details of the response characteristics of the WDD device 228. As will be seen herein below, the difference between the secondary lobe or side-lobe component of each adjacent optical carrier (those in the neighbourhood of system frequencies F^*_{i+1}
- 20 and F^*_{i-1}) determines the degree to which optical carrier i is centered about corresponding system frequency F^*_i .

- Each of the middle optical receivers R_i ($1 \leq i \leq N$) is connected to three tone detectors D_i^{-1} , D_i^0 and D_i^{+1} .
- 25 Since laser L_i radiates at a carrier frequency F_i (which is in the neighbourhood of both the corresponding system frequency F^*_i and the corresponding channel center frequency $F_{ch,i}$), and since the radiated signal contains a component at tone frequency T_i , it follows that the
- 30 electrical signal at the output of optical receiver R_i will also contain a component at tone frequency T_i . Accordingly, tone detector D_i^0 is adapted to measure the

amplitude of tone frequency T_i in the signal processed by receiver R_i . The output of tone detector D_i^0 is used as the previously described measured carrier amplitude AV_i which is fed to laser controller C_i associated with optical carrier i .

Furthermore, it is noted that since the open loop frequency F_i^{open} deviates from the corresponding system frequency F_i^* (and the corresponding channel center frequency $F_{\text{ch},i}$), the signals processed by neighbouring receivers R_{i-1} and R_{i+1} will initially contain an arbitrary level of the tone frequency T_i . For exactly the same reason, the signal processed by receiver R_i will initially detect an output with slightly more or slightly less of each of the tone frequencies T_{i-1} and T_{i+1} and, as will be seen herein below, these components will tend towards a low, balanced amplitude upon convergence of the frequency control loop. Accordingly, each pair of tone detectors D_i^{-1} and D_i^{+1} is adapted to measure the amplitude of tone frequencies T_{i-1} and T_{i+1} , respectively, in the signal processed by receiver R_i .

Frequency discrimination is achieved as follows. In order to determine whether the signal received by each receiver R_i is truly centered within the associated optical channel, a comparator H_i is provided for each receiver R_i . Comparator H_i has one input connected to the output of tone detector D_{i-1}^{+1} (which is connected to receiver R_{i-1}) and another input connected to the output of tone detector D_{i+1}^{-1} (which is connected to receiver R_{i+1}). In other words, comparator H_i compares the amplitude of the component at tone frequency T_i of the

optical signal in each of the adjacent optical channels. The output of each comparator H_i , $1 \leq i \leq N$, is the previously described measured amplitude offset AO_i , which is fed to laser controller C_i associated with optical carrier i .

It is noted that comparators H_1 and H_N are a special case because they require measurements performed outside the N middle optical channels. Specifically, comparator H_1 accepts one input from tone detector D_2^{-1} and a second input from an additional tone detector D_0^{+1} connected to receiver R_0 (centered about a frequency of $F^*_1 - 100$ GHz), while comparator H_N accepts one input from tone detector D_{N-1}^{+1} and a second input from an additional tone detector D_{N+1}^{-1} connected to receiver R_{N+1} (centered about a frequency of $F^*_N + 100$ GHz).

Operation of the amplitude and frequency control loops involving controller C_i is now described by way of a non-limiting example. Initially, under open loop conditions, controller C_i sets the amplitude adjustment signal ΔA_i to a value such that laser L_i radiates at a relatively low power level. At this low power level, the frequency control loop is used to tune the carrier frequency F_i of laser L_i to the appropriate system frequency F^*_i . Specifically, laser controller C_i compares the measured amplitude offset AO_i at the output of comparator H_i to a desired offset AO^*_i . The result of this comparison is the frequency adjustment signal ΔF_i , which is amplified and fed to suitable frequency correction circuitry in laser L_i .

Figure 1 displays 12 small graphs (a-l) showing the time course of various physiological variables during a 10-minute period. The variables are: a) Heart rate (b/min), b) Blood pressure (mmHg), c) Stroke volume (l/min), d) Cardiac output (l/min), e) Systemic vascular resistance (dyne/cm²), f) Pulmonary vascular resistance (dyne/cm²), g) Pulmonary artery pressure (mmHg), h) Right ventricular pressure (mmHg), i) Left ventricular pressure (mmHg), j) Aortic pressure (mmHg), k) Left ventricular stroke volume (l/min), and l) Left ventricular stroke volume index (l/min/m²). Each graph shows a baseline value and a response to a stimulus, with error bars indicating standard error.

30

Once the carrier frequency F_i has been adjusted to match the corresponding system frequency F_i^* , the next step is

to set the amplitude A_i using the amplitude control loop. To this end, laser controller C_i compares the measured carrier amplitude AV_i to a desired carrier amplitude AV^*_i and the difference is used to create the d.c. component of the amplitude adjustment signal ΔA_i . Specifically, the difference between AV_i and AV^*_i is amplified and becomes the control for the d.c. bias (or d.c. drive current) through laser L_i , thus causing it to lase at an optical power related to that drive current. This d.c. bias is combined with a small signal at tone frequency T_i to produce the a.c. component of the amplitude adjustment signal ΔA_i , thereby inducing a small amount of intensity modulation on the optical output of laser L_i which, in turn, provides tone T_i to the tone detectors D_{i-1}^{+1} , D_i^0 , D_{i+1}^{-1} , via the WDD device 228 and the optical receivers R_{i-1} , R_i , R_{i+1} in order to enable the optical frequency discrimination process.

At first, laser controller C_i will detect a low power output based on the difference between AV_i and AV^*_i and, as a result, the amplitude adjustment signal ΔA_i will be steadily increased. This action may consequently skew the carrier frequency F_i , but because the latter is under control of the frequency feedback loop, any drift in the carrier frequency F_i with respect to the corresponding system frequency F^*_i will be cancelled out by a compensatory change to the frequency control conditions.

The exact technique for correcting carrier frequency F_i using the frequency adjustment signal ΔF_i depends on the design of laser L_i . Any suitable technique can be used for this purpose, including changing the substrate

temperature, changing the bias voltage on (or current through) a third electrode connected to a series cavity, etc. In the case of a thermally tuned laser, the frequency adjustment signal ΔF_i would be amplified and
5 injected as a reference level into a Peltier cooler control circuit, causing an offset in the stabilized temperature of laser L_i . The magnitude of the adjustments would reduce to almost zero as laser L_i tunes its frequency of optical radiation to the required system
10 frequency F^*_i .

As has been mentioned herein above, other WDD devices with different channel response shapes from those illustrated in Fig. 3A are suitable for use with the
15 present invention. For example, it is within the scope of the present invention to use a WDD device 228 having the characteristics shown in part in Fig. 3B. In this case, channel center frequencies $F_{ch,8}$, $F_{ch,9}$ and $F_{ch,10}$ are still identical to system frequencies F^*_8 , F^*_9 and
20 F^*_{10} , and the response of each optical channel overlaps the adjacent ones in the manner of Fig. 3A. However, in this case, the shape of each response consists of a single main lobe with distant well-suppressed or non-existent side lobes. Still, each response again has
25 opposite slopes when measured at the center frequencies of the two adjacent optical channels. Each of the remaining optical channels (not shown) may have a similarly shaped response, but shifted by 100 GHz so that it would be centered about the appropriate system
30 frequency F^*_i associated with optical carrier i . Operation of each laser controller C_i is as described herein above.

5

15

30

port is associated with an optical channel having an optical pass band centered about a unique channel center frequency $F_{ch,i}$. In the specific embodiment of Fig. 4, the channel center frequencies $F_{ch,i}$ (which are associated with the N middle ports P_i , $1 \leq i \leq N$) are offset from the system frequencies F^*_i such that the peak responsivity of a given channel i occurs at some point (e.g., half way) between system frequencies F^*_i and F^*_{i+1} . Port P_0 of the WDD device 428 is associated with an optical channel centered about frequency $F^*_1 - 50$ GHz.

Stated differently, system frequency F^*_i will fall somewhere between channel center frequencies $F_{ch,i-1}$ and $F_{ch,i}$. Hence, by comparing the amplitude of tone T_i as received in the two channels centered about channel center frequencies $F_{ch,i-1}$ and $F_{ch,i}$, a sensitive optical frequency discriminator can be produced. Since these tone components are only half as far away from the peak of the main lobe of channel center frequency $F_{ch,i}$ (when compared to the embodiment of Fig. 2), the detected amplitude levels for the components providing the discrimination function will be substantially higher, resulting in lower demands on the optical receivers and/or the need to tap less light at the output splitter 224.

Reference is made to Fig. 5, wherein channel center frequencies $F_{ch,8}$, $F_{ch,9}$ and $F_{ch,10}$ are shown for the case where each channel has a main lobe and symmetrically disposed side lobes. As can be seen, since the main lobe of a given optical channel i is symmetric on either side of the channel center frequency $F_{ch,i}$, the carrier

frequency F_i will, when tuned to the corresponding system frequency F^*_i , undergo the same amount of attenuation when measured at the center frequency of channel $i - 1$ or at the center frequency of channel i . Of course, it

5 should be understood that different WDD devices can be used and will lead to different embodiments of the invention, depending on the inter-channel spacing, on the shape of each individual channel response and on variations in the response shape among optical channels.

10 For example, it is within the scope of the invention to use a WDD device with individual channel responses each consisting of a wide main lobe and distant or even non-existent side lobes.

15 Continuing with the description of Fig. 4, each output port P_i ($0 \leq i \leq N$) of the WDD device 428 is connected to a respective low-bandwidth optical receiver R_i ($0 \leq i \leq N$), which is adapted to provide opto-electronic conversion functionality. Each of the optical receivers

20 R_i for which $1 \leq i \leq N$ outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about the corresponding channel center frequency $F_{ch,i}$ which, in the embodiment of Fig. 4, corresponds to system frequency F^*_i augmented by half of

25 the channel spacing. Thus, each optical receiver R_i outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about $F^*_i + 50$ GHz. In addition, output port P_0 is connected to low-bandwidth optical receiver R_0 , which provides opto-

30 electronic conversion of the portion of the multi-carrier optical signal centered at $F^*_1 - 50$ GHz.

Each of the middle optical receivers R_i for which $1 \leq i \leq N$ is connected to two tone detectors D_i^0 and D_i^{+1} . Tone detector D_i^0 is adapted to measure the amplitude of tone frequency T_i in the signal processed by receiver R_i , while tone detector D_i^{+1} is adapted to measure the amplitude of tone frequency T_{i+1} in the signal processed by receiver R_i .

Due to the response characteristics of the WDD device 428, the measured amplitude offset AO_i and the measured carrier amplitude AV_i need to be generated in a slightly different manner, when compared to the way in which these signals were generated in the embodiment of Fig. 2. Firstly, in order to determine whether the signal received by each receiver R_i is truly centered between channel center frequencies $F_{ch,i-1}$ and $F_{ch,i}$, a comparator H_i is provided for each receiver R_i . Comparator H_i has one input connected to the output of tone detector D_{i-1}^{+1} (which is connected to receiver R_{i-1}) and another input connected to the output of tone detector D_i^0 (which is connected to receiver R_i). In other words, comparator H_i evaluates the difference between the amplitude of the component at tone frequency T_i of the optical signal in the channel centered about frequency $F_{ch,i}$ and the amplitude of the component at tone frequency T_i of the optical signal in the channel centered about frequency $F_{ch,i-1}$. The output of each comparator H_i , $1 \leq i \leq N$, is the aforescribed measured amplitude offset AO_i , which is fed to laser controller C_i associated with optical carrier i .

Also, due to the offset in the channel responses of the WDD device 428, it is noted that the power of a given optical carrier cannot be estimated directly from measuring the amplitude of that optical carrier at the center frequency of one of the optical channels. In order to obtain a reliable measurement of the presence of tone T_i , a power combiner 450_i combines the amplitude measured by the two tone detectors associated with tone T_i , namely tone detector D_i^0 and tone detector D_{i-1}^{+1} . The output of power combiner 450_i is used as the previously described measured carrier amplitude AV_i which is fed to laser controller C_i associated with optical carrier i . Alternatively, as indicated previously, a conventional amplitude stabilization loop based on the use of a back facet monitor diode with each laser can be implemented with no loss effect on the ability of the frequency control loop to lock the carrier frequencies.

Operation of the amplitude and frequency control loops involving controller C_i is now described by way of a non-limiting example. Initially, under open loop conditions, controller C_i sets the amplitude adjustment signal ΔA_i to a low value such that laser L_i radiates at a relatively low power level. At this low power level, the frequency control loop is used to tune the carrier frequency F_i of laser L_i to the appropriate system frequency F_i^* . Specifically, laser controller C_i compares the measured amplitude offset AO_i at the output of comparator H_i to a desired offset AO_i^* . The result of this comparison is the frequency adjustment signal ΔF_i , which is fed to suitable frequency correction circuitry in laser L_i .

5

20

25

current) through laser L_i , thus causing it to lase at an optical power related to that drive current. This d.c. bias is combined with a small signal at tone frequency T_i to produce the a.c. component of the amplitude adjustment
5 signal ΔA_i , thereby inducing a small amount of intensity modulation on the optical output of laser L_i .

At first, laser controller C_i will detect a low power output and, as a result, the amplitude adjustment signal
10 ΔA_i will be steadily increased. This action may consequently skew the carrier frequency F_i , but because the latter is under control of the frequency feedback loop, any drift in the carrier frequency F_i with respect to the corresponding system frequency F^*_i will be
15 compensated for by a change to the frequency control conditions.

The exact technique for correcting carrier frequency F_i using the frequency adjustment signal ΔF_i depends on the
20 design of laser L_i . Any suitable technique can be used for this purpose, including changing the substrate temperature, changing the bias voltage on (or current through) a third electrode connected to a series cavity, etc. In the case of a thermally tuned laser, the
25 frequency adjustment signal ΔF_i would be amplified and injected as a reference level into a Peltier cooler control circuit, causing an offset in the stabilized temperature of laser L_i . The magnitude of the adjustments would reduce to almost zero as laser L_i tunes
30 its frequency of optical radiation to the required system frequency F^*_i .

A third embodiment of the multi-carrier optical signal source of the present invention is now described with reference to Fig. 6. This embodiment uses yet another wavelength division demultiplexing (WDD) device 628 as the frequency discriminator. The WDD device 628 has a channel separation of one half of the intended optical grid output separation (i.e. 50 GHz for a 100 GHz grid) and has an offset of one half of the WDD channel spacing (25 GHz for a 50 GHz WDD).

10

Each of the lasers L_i outputs a single-carrier optical signal which is fed to a common broad-lobed wavelength division multiplexing (WDM) device 222. The WDM device 222 combines the N single-carrier optical signals into a multi-carrier optical signal. The output of the WDM device 222 is connected, via a splitter 224, both to the core network 226 and to the WDD device 628. The splitter 224 may suitably divert between 5 and 10 % of the optical power of the multi-carrier optical signal towards the WDD device 628, while feeding the rest of the power to the core network 226. Of course, those skilled in the art will appreciate that other power splitting ratios are possible.

20

The WDD device 628 is substantially a multi-channel optical filter. In the embodiment of Fig. 6, the WDD device 628 has $2N$ output ports P_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$. Specifically, each port is associated with an optical channel having an optical pass band centered about a unique channel center frequency $F_{ch,2i+k}$. In the specific embodiment of Fig. 6, the channel center frequencies $F_{ch,2i+k}$ correspond to $F_i^* + ((-1)^k \cdot 25)$

30

GHz. In other words, system frequency F^*_i falls mid-way between channel center frequency $F_{ch,2i-1}$ and channel center frequency $F_{ch,2i}$.

- 5 This is illustrated in Fig. 7, where channel center frequencies $F_{ch,17}$, $F_{ch,18}$ and $F_{ch,19}$ are shown. It is seen that each system frequency is located half way between two channel center frequencies which are uniquely associated with that system frequency. As can be seen,
- 10 when the main lobe of a given optical channel is symmetric on either side of its channel center frequency, the optical carrier at frequency F_i will, when tuned to the corresponding system frequency F^*_i , undergo the same amount of attenuation when measured at the center
- 15 frequency of either channel $2i-1$ or channel $2i$. Of course, it should be understood that different WDD devices can be used and will lead to different embodiments of the invention, depending on the inter-channel spacing, on the shape of each individual channel response and on variations in the response shape among
- 20 optical channels.

- Continuing with the description of Fig. 6, each output port P_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, of the WDD device 628
- 25 is connected to a respective low-bandwidth optical receiver R_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, which is adapted to provide opto-electronic conversion functionality. Each of the optical receivers R_{2i+k} outputs a low-bandwidth electrical version of the portion of the multi-
- 30 carrier optical signal centered about the corresponding channel center frequency $F_{ch,2i+k}$ which, in the embodiment of Fig. 6, corresponds to system frequency F^*_i

adjusted by $(-1)^k \cdot 25$ GHz. That is to say, each optical receiver R_{2i+k} outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about $F_i + (-1)^k \cdot 25$ GHz.

5

Each of the optical receivers R_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, is connected to a respective tone detector D_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$. Tone detectors D_{2i} and D_{2i+1} are both adapted to measure the amplitude of same tone frequency T_i in the signal processed by the respective receiver. In order to determine whether the optical carrier at frequency F_i undergoes the same amount of attenuation when measured at the center frequency of channel $2i-1$ as at the center frequency of channel $2i$, a comparator H_i is provided for each pair of receivers R_{2i-1} and R_{2i} . Comparator H_i has one input connected to the output of tone detector D_{2i-1} (which is connected to receiver R_{2i-1}) and another input connected to the output of tone detector D_{2i} (which is connected to receiver R_{2i}). In other words, comparator H_i evaluates the difference between the amplitude of the component at tone frequency T_i of the optical signal in the channel centered about frequency $F_{ch,2i-1}$ and the amplitude of the component at tone frequency T_i of the optical signal in the channel centered about frequency $F_{ch,2i}$. The output of each comparator H_i , $1 \leq i \leq N$, is the previously described measured amplitude offset AO_i , which is fed to laser controller C_i associated with optical carrier i .

Also, due to the offset in the channel responses of the WDD device 628, it is noted that the power of a given optical carrier cannot be estimated directly from

30

measuring the amplitude of that optical carrier at the center frequency of one of the optical channels. In order to obtain a reliable measurement of the presence of tone T_i , a power combiner 450_i combines the amplitude
5 measured by the two tone detectors associated with tone T_i , namely tone detector D_{2i-1} and tone detector D_{2i} . The output of power combiner 450_i is used as the previously described measured carrier amplitude AV_i which is fed to laser controller C_i associated with optical
10 carrier i .

Operation of the amplitude and frequency control loops involving controller C_i is now described by way of a non-limiting example. Initially, under open loop conditions,
15 controller C_i sets the amplitude adjustment signal ΔA_i to a low value such that laser L_i radiates at a relatively low power level. At this low power level, the frequency control loop is used to tune the carrier frequency F_i of laser L_i to the appropriate system frequency F^*_i .
20 Specifically, laser controller C_i compares the measured amplitude offset AO_i at the output of comparator H_i to a desired offset AO^*_i . The result of this comparison is the frequency adjustment signal ΔF_i , which is fed to suitable frequency correction circuitry in laser L_i .

25

The desired offset AO^*_i depends on the frequency response of the WDD device 628 for each individual optical channel. For example, in the case where each main lobe is symmetric about the corresponding channel center
30 frequency and where channel center frequency $F_{ch,2i+k}$ corresponds to $F^*_i + (-1)^k \cdot \frac{1}{4}$ of the channel spacing (such as is the case with the individual channel

responses of Fig. 7), then the desired offset AO^*_i is zero. That is to say, the carrier frequency F_i is equal to the corresponding system frequency F^*_i only when the amplitude of tone frequency T_i is the same in the signal
5 processed by receiver R_{2i-1} as it is in the signal processed by receiver R_{2i} . In other cases, the main lobes might not be symmetric about their channel center frequencies, but the shape of each response would be known in advance and hence it would be possible to
10 determine the magnitude of the offset AO^*_i which should exist between the amplitude of tone frequency T_i in the signal processed by receiver R_{2i-1} and the amplitude of tone frequency T_i in the signal processed by receiver R_{2i} .
15
Once the carrier frequency F_i has been adjusted to match the corresponding system frequency F^*_i , the next step is to set the amplitude A_i using the amplitude control loop. To this end, laser controller C_i compares the measured
20 carrier amplitude AV_i to a desired carrier amplitude AV^*_i and the difference is used to create the d.c. component of the amplitude adjustment signal ΔA_i . Specifically, the difference between AV_i and AV^*_i is amplified and becomes the control for the d.c. bias (or d.c. drive
25 current) through laser L_i , thus causing it to lase at an optical power related to that drive current. This d.c. bias is combined with a small signal at tone frequency T_i to produce the a.c. component of the amplitude adjustment signal ΔA_i , thereby inducing a small amount of intensity
30 modulation on the optical output of laser L_i .

At first, laser controller C_i will detect a low power output and, as a result, the amplitude adjustment signal ΔA_i will be steadily increased. This action may consequently skew the carrier frequency F_i , but because
5 the latter is under control of the frequency feedback loop, any drift in the carrier frequency F_i with respect to the corresponding system frequency F^*_i will be compensated for by a change to the frequency control conditions.

10

The exact technique for correcting carrier frequency F_i using the frequency adjustment signal ΔF_i depends on the design of laser L_i . Any suitable technique can be used for this purpose, including changing the substrate
15 temperature, changing the bias voltage on (or current through) a third electrode connected to a series cavity, etc. In the case of a thermally tuned laser, the frequency adjustment signal ΔF_i would be amplified and injected as a reference level into a Peltier cooler
20 control circuit, causing an offset in the stabilized temperature of laser L_i . The magnitude of the adjustments would reduce to almost zero as laser L_i tunes its frequency of optical radiation to the required system frequency F^*_i .

25

Whilst the above operation has been described in the context of accurately modulated low-modulation tones and tone receivers, it is to be understood that, if the free-running precision of the lasers L_i and the pass-band
30 characteristics of the WDD device 628 are such that only insignificant optical powers can turn up in the wrong lobe, then the tones can be eliminated and the tone

detectors D_i can be replaced by simple d.c. optical power monitors, since there is no longer any need to be able to discriminate the presence of more than one optical carrier in a particular optical channel output by the WDD
5 device via ports P_i .

A fourth embodiment of the multi-carrier optical signal source of the present invention is now described with reference to Fig. 8. In this embodiment, which is a
10 variation of the embodiment of Fig. 6, tones are used to tune the carrier frequencies F_i to the system frequencies F^*_i , but the tones are subsequently removed in order not to disturb the traffic on each optical carrier. The tones may thereafter be reinstated under certain
15 conditions to be described herein below.

With reference to Fig. 8, each output port P_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, of the WDD device 628 is connected to a respective low-bandwidth optical receiver R_{2i+k} , $1 \leq i \leq$
20 N , $-1 \leq k \leq 0$, which is adapted to provide opto-electronic conversion functionality. Each of the optical receivers R_{2i+k} outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about the corresponding channel center
25 frequency $F_{ch,2i+k}$ which, in the embodiment of Fig. 6, corresponds to system frequency F^*_i adjusted by $(-1)^k \cdot 25$ GHz. That is to say, each optical receiver R_{2i+k} admits a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about $F^*_i +$
30 $(-1)^k \cdot 25$ GHz.

Each of the optical receivers R_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, is connected to a respective power monitor 860_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$ and to a respective tone detector D_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$. Power monitor 860_{2i+k} is adapted to measure the power in the signal admitted by the respective receiver. Tone detectors D_{2i-1} and D_{2i} are adapted to measure the amplitude of the same tone frequency T_i in the signals processed by the respective receivers.

10

The outputs of power monitors 860_{2i-1} , 860_{2i} and the outputs of tone detectors D_{2i-1} , D_{2i} are connected to four inputs of a controllable switch 870_i . Switch 870_i has two outputs, each of which is connected to separate inputs of a comparator H_i and a power combiner 450_i . Switch 870_i functions in two states; in the first state, switch 870_i connects the output of tone detector D_{2i-1} to a first input of comparator H_i and to a first input of power combiner 450_i , and switches the output of tone detector D_{2i} to a second input of comparator H_i and to a second input of power combiner 450_i . In the second state, switch 870_i connects the output of power monitor 860_{2i-1} to the first input of comparator H_i and to the first input of power combiner 450_i , and switches the output of power monitor 860_{2i} to the second input of comparator H_i and to the second input of power combiner 450_i .

Thus, when switch 870_i operates in the first state, comparator H_i evaluates the difference between the amplitude of the component at tone frequency T_i of the optical signal in the channel centered about frequency

$F_{ch,2i-1}$ and the amplitude of the component at tone frequency T_i of the optical signal in the channel centered about frequency $F_{ch,2i}$. On the other hand, when switch 870_i operates in the second state, comparator H_i evaluates the difference between the power of the optical signal in the channel centered about frequency $F_{ch,2i-1}$ and the power of the optical signal in the channel centered about frequency $F_{ch,2i}$. In each case, the output of each comparator H_i , $1 \leq i \leq N$, is the previously described measured amplitude offset AO_i , which is fed to laser controller C_i associated with optical carrier i . Additionally, the output of each comparator H_i is fed to a first input of a respective out-of-range detector 880_i.

Also, when switch 870_i operates in the first state, power combiner 450_i combines the amplitude measured by the two tone detectors associated with tone T_i , namely tone detector D_{2i-1} and tone detector D_{2i} . On the other hand, when switch 870_i operates in the second state, power combiner 450_i combines the amplitude measured by power monitor 860_{2i-1} and power monitor 860_{2i}. In each case, the output of power combiner 450_i is used as the previously described measured carrier amplitude AV_i which is fed to laser controller C_i associated with optical carrier i . Additionally, the output of each power combiner 450_i is fed to a second input of the respective out-of-range detector 880_i.

Out-of-range detector 880_i, which is connected to comparator H_i and to power combiner 450_i, is further connected to a control port of switch 870_i. Out-of-range

detector 880_i functions to monitor the readings from comparator H_i and power combiner 450_i and to control the state of switch 870_i as a function of these readings. Initially, switch 870_i is set to the first state. If the
5 readings are stable, then out-of-range detector 880_i toggles the state of switch 870_i so that it enters the second state. If the readings eventually become unstable again, then out-of-range detector 880_i is operable to toggle the state of switch 870_i back to the first state
10 and to wait for a stable condition to arise again.

It is noted that when switch 870_i is in the second state, control of system parameters related to optical carrier i is no longer performed as a function of the presence or
15 absence of tone T_i in the optical channels centered about frequencies $F_{ch,2i-1}$ and $F_{ch,2i}$. Hence, when switch 870_i is in the second state, it is no longer necessary to modulate the output of laser L_i with tone T_i . To this end, out-of-range detector 880_i is provided with a
20 connection to a respective switch 890_i that is adapted to disable application of tone T_i to the amplitude control circuit of laser L_i . This has the added benefit of keeping the output of laser L_i free of control signals once stability has been achieved. Switch 890_i may be
25 integral with laser controller C_i . Alternatively, the tones may continue to be applied by the lasers L_i , in which case it is advantageous to use a low modulation depth for the tones in order to limit the optical impairment in the transmission system.

30

Operation of the amplitude and frequency control loops involving controller C_i is now described by way of a non-

limiting example. Initially, under open loop conditions, out-of-range detector 880_i sets the switch 870_i to the first state (in which tone detection is used for control purposes) and controller C_i sets the amplitude adjustment signal ΔA_i to a low value such that laser L_i radiates at a relatively low power level. At this low power level, the frequency control loop is used to tune the carrier frequency F_i of laser L_i to the appropriate system frequency F*_i. Specifically, laser controller C_i compares the measured amplitude offset AO_i at the output of comparator H_i to a desired offset AO*_i. The result of this comparison is the frequency adjustment signal ΔF_i , which is fed to suitable frequency correction circuitry in laser L_i.

The desired offset AO*_i depends on the frequency response of the WDD device 628 for each individual optical channel. For example, in the case where each main lobe is symmetric about the corresponding channel center frequency and where channel center frequency F_{ch,2i+k} corresponds to $F_i^* + (-1)^k \cdot \frac{1}{4}$ of the channel spacing (such as is the case with the individual channel responses of Fig. 7), then the desired offset AO*_i is zero. That is to say, the carrier frequency F_i is equal to the corresponding system frequency F*_i only when the amplitude of tone frequency T_i is the same in the signal processed by receiver R_{2i-1} as it is in the signal processed by receiver R_{2i}. In other cases, the main lobes might not be symmetric about their channel center frequencies, but the shape of each response would be known in advance and hence it would be possible to determine the magnitude of the offset AO*_i which should

exist between the amplitude of tone frequency T_i in the signal processed by receiver R_{2i-1} and the amplitude of tone frequency T_i in the signal processed by receiver R_{2i} .

5

Once the carrier frequency F_i has been adjusted to match the corresponding system frequency F^*_i , the next step is to set the amplitude A_i using the amplitude control loop. To this end, laser controller C_i compares the measured carrier amplitude AV_i to a desired carrier amplitude AV^*_i and the difference is used to create the d.c. component of the amplitude adjustment signal ΔA_i . Specifically, the difference between AV_i and AV^*_i is amplified and becomes the control for the d.c. bias (or d.c. drive current) through laser L_i , thus causing it to lase at an optical power related to that drive current. This d.c. bias is combined with a small signal at tone frequency T_i to produce the a.c. component of the amplitude adjustment signal ΔA_i , thereby inducing a small amount of intensity modulation on the optical output of laser L_i .

At first, laser controller C_i will detect a low power output and, as a result, the amplitude adjustment signal ΔA_i will be steadily increased. This action may consequently skew the carrier frequency F_i , but because the latter is under control of the frequency feedback loop, any drift in the carrier frequency F_i with respect to the corresponding system frequency F^*_i will be compensated for by a change to the frequency control conditions.

30

The exact technique for correcting carrier frequency F_i using the frequency adjustment signal ΔF_i depends on the design of laser L_i . Any suitable technique can be used for this purpose, including changing the substrate
5 temperature, changing the bias voltage on (or current through) a third electrode connected to a series cavity, etc. In the case of a thermally tuned laser, the frequency adjustment signal ΔF_i would be amplified and injected as a reference level into a Peltier cooler
10 control circuit, causing an offset in the stabilized temperature of laser L_i . The magnitude of the adjustments would reduce to almost zero as laser L_i tunes its frequency of optical radiation to the required system frequency F^*_i .

15 Once an optical carrier has been "locked" in this way by the amplitude and frequency control loops, each comparator H_i will yield a result that is close to the respective desired offset AO^*_i and each power combiner
20 450_i will be giving a high reading. Under these conditions, out-of-range detector 880_i will toggle the state of switch 870_i so that what is fed to comparator H_i and power combiner 450_i is the output of power monitors 8602_{i-1} and 8602_i rather than the output of tone
25 detectors D2_{i-1} and D2_i. Once this switching has been completed the tone input to laser L_i can be turned off, since it no longer serves any purpose, and hence the locked optical carrier is now tone-free.

30 It is noted that since a locked optical carrier may be disturbed by a spurious optical signal from a neighbouring but unlocked optical carrier, the individual

out-of-range detectors 880_i may be cross-coupled so that, even once the optical carrier is locked, the state of switch 870_i is not toggled to the second state and tone T_i is not turned off unless these neighbouring optical carriers are also locked. In the event that an optical carrier becomes unlocked, then tone T_i is re-inserted and switch 870_i is commanded to return to the first state, in which the outputs of tone detectors D_{2i-1} and D_{2i} are connected to comparator H_i and to power combiner 450_i .

10 In this sense, "neighbouring" is meant to encompass the maximum amount of optical channels over which may range the divergence of the frequency of a given optical carrier.

15 The above embodiments have assumed that the carrier frequencies F_i emitted by the lasers L_i are in the neighbourhood of the corresponding system frequencies F^*_i . Although this may be a plausible assumption in many cases, there are situations in which the assumption is

20 not valid. Such situations require an ability to pull in optical sources that are out of sequence or are exhibiting optical frequency offsets in excess of one frequency channel. For example, Fig. 10 shows the case where carrier frequency F_J , which was previously assumed

25 to appear in the neighbourhood of system optical frequency F^*_J , instead appears in the vicinity of system optical frequency F^*_{J+2} . What is required is a coarse wavelength capture mechanism to bring F_J to within the neighbourhood of system optical frequency F^*_J , following

30 which the system of Fig. 2 could be reverted to.

Accordingly, with reference to Fig. 9, there is shown a fifth embodiment of the present invention, which is similar to the embodiment of Fig. 2 but includes a coarse wavelength capture mechanism, comprising a set of first
5 splitters 910, a combiner 920, a tone detection unit 940 and a control unit 950. It will be noted that the splitter 224 of Fig. 2 has been replaced in Fig. 9 by the set of first splitters 910, each of which is connected between a respective one of the lasers L_i and the WDM
10 device 222. Each splitter 910 may suitably divert between 5 and 10 % of the optical power of the respective single-carrier optical signal towards a respective input of the combiner 920, while feeding the rest of the power to the WDM device 222 and the core network. Of course,
15 those skilled in the art will appreciate that other power splitting ratios are possible.

The combiner 920 multiplexes the individual optical signals into a multi-carrier optical signal provided to
20 the input of the WDD device 228, which is substantially a multi-channel optical filter. As already described with reference to Fig. 2, the WDD device 228 has $N+2$ output ports P_i , $0 \leq i \leq N+1$, one for each of $N+2$ optical channels of width 100 GHz, although it should be
25 understood that the coarse wavelength capture mechanism variation being described here can be applied to any of the previously described example embodiments. Each port is associated with an optical channel having an optical pass band centered about a unique channel center
30 frequency $F_{ch,i}$. In the specific embodiment of Fig. 2, the channel center frequencies $F_{ch,i}$ (which are associated with the N middle ports P_i , $1 \leq i \leq N$)

correspond to system frequencies F^*_i . The two other ports of the WDD device 228, namely P_0 and P_{N+1} , are associated with optical channels centered about frequencies $F^*_1 - 100$ GHz and $F^*_N + 100$ GHz, respectively.

Each output port P_i ($0 \leq i \leq N+1$) of the WDD device 228 is connected to a respective low-bandwidth optical receiver, denoted R_i for $0 \leq i \leq N+1$, which is adapted to provide opto-electronic conversion functionality. Each of the "middle" optical receivers (i.e., those receivers R_i for which $1 \leq i \leq N$) outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about the corresponding channel center frequency $F_{ch,i}$ which, in the embodiment of Fig. 9, corresponds to system frequency F^*_i . Receivers R_0 and R_{N+1} output a low-bandwidth version of the portion of the multi-carrier optical signal centered about $F^*_1 - 100$ GHz and $F^*_N + 100$ GHz, respectively.

As with the embodiment of Fig. 2, each of the optical receivers R_i ($1 \leq i \leq N$) is connected to three tone detectors D_i^{-1} , D_i^0 and D_i^{+1} . Additionally, in the embodiment of Fig. 9, the electrical output of each of the middle optical receivers R_i ($1 \leq i \leq N$) is also buffered and diverted to the tone detection unit 940 at a respective electrical connection point. The tone detection unit 940 may include a set of tunable filters along with a bank of tone detectors. The purpose of the tone detection unit 940 is to determine, through detection of the tones T_i , the port $P_{F^0(i)}$ in which each

carrier frequency F_i appears strongest. This information is fed to the control unit 950.

It is noted each laser L_i has to be given a broadband
5 connection into the WDD device 228, since its carrier
frequency F_i must be detectable if ever it appears at the
"wrong" output port of the WDD device 228 (i.e., if $P_{f^0}(i)$
is different from P_i). It would not be possible to
achieve a broadband connection if the splitter 224 of
10 Fig., 2 were used as positioned therein, since if laser
 L_i were sufficiently off-tune that F_i were to appear at
the wrong port, it would have been blocked by the WDM
device 222 and it would not be possible for the tone
detection unit 940 to detect this fact. The use of a
15 broadband passive combiner 920, on the other hand, allows
erroneously positioned carrier frequencies to appear at
"wrong" output ports of the WDD device 228. In addition,
various optical carrier output multiplexing arrangements
can be accommodated, including the example shown in Fig
20 2B.

The control unit 950 is adapted to determine, based on
information received from the tone detection unit 940,
the difference between $P_{f^0}(i)$ and P_i . The control unit
25 950 is operable to generate a compensatory bias signal
which is fed to the corresponding laser controller C_i .
Laser controller C_i is adapted to add the signal received
from the control unit 950 to the previous value of the
d.c. bias signal it was sending to laser L_i . This is an
30 attempt to cause the carrier frequency F_i to appear at
port P_i (but this attempt may be unsuccessful as the
carrier frequency F_i may instead appear at port $P_{f^1}(i)$,

which is closer to, but not coincident with, port P_i . In this case, the process repeats in an iterative fashion, until the error is reduced such that the initially out-of-place optical carrier appears within the correct
5 lobe.)

In operation, and with reference to the example scenario in Fig. 10, the coarse wavelength capture mechanism provides approximate wavelength tuning by allowing laser
10 L_J to be synchronized from an initial starting position that may be several (in this case +2) lobes off-tune. The fact that carrier frequency F_J appears at port $P_{f^0(J)} = P_{J+2}$ is detected by the tone detection unit 940 and an appropriate compensatory signal will be generated by the
15 control unit 950. During this time, it is within the scope of the invention to disable adjustments that may be based on any difference between AO_J and AO^*J .

If, as a result of applying the compensatory signal to
20 laser L_J via controller C_J , carrier frequency F_J now appears at port P_J , then the frequency control loop of Fig. 2 can take over and lock F_J into position with respect to the corresponding system frequency F^*J . However, if the compensatory signal has been insufficient
25 or excessive and laser L_J emits a carrier frequency F_J which - although nearer the correct position - nonetheless still appears strongest at a port $P_{f^1(J)}$ that is not equal to P_J , then the coarse wavelength capture mechanism will again detect this fact and will cause the
30 generation of another compensatory signal in an iterative process.

Fig. 11 shows a sixth embodiment of the present invention, comprising an output switch 1110 that intercepts the optical path leading from each laser L_i to the WDM device 222 or any other optical carrier multiplexing structure which may be required, including straightforward unmultiplexed outputs. Alternatively, there may be provided a set of individual optical switches, each in the optical path of a respective one of the lasers L_i . It is noted that the output switch 1110 is located after the splitters 910 to allow the optical signal from each of the lasers L_i to circulate through the frequency control loop, but is located before the WDM device 222 to prevent the optical signal from selected ones of the lasers L_i to exit the multi-carrier optical signal source, under control of a control signal received from a control unit 1150 via a control line 1120.

The control unit 1150 may be based on the control unit 950 of Fig. 9, but is additionally adapted to prevent an optical carrier that is not locked (i.e., an optical carrier for which AO_i is not to within a predetermined threshold of AO^*_i) from exiting the multi-carrier optical signal source 100. This advantageously prevents unlocked optical carriers from interfering with locked optical carriers. Specifically, an optical carrier which is close to lock, but is not yet locked, would pass through the WDM device 228 unhindered but may be sufficiently off-tune that, when it is modulated, the modulation sidebands overlap those of an adjacent locked optical carrier. This situation is averted by disconnecting such "almost-locked" optical carriers from the output until

they are locked and by disconnecting them from the output if they become unlocked again.

Those skilled in the art will appreciate that although the sixth embodiment illustrated in Fig. 11 is based on the fifth embodiment shown in Fig. 9, it is within the scope of the invention to supply an output switch 1110 with any of the previous embodiments, with or without a coarse wavelength capture mechanism.

10

Fig. 12 shows a seventh embodiment of the present invention, in which the multi-carrier outputs of two (or more) multi-carrier optical signal sources 1210_A, 1210_B of the type described previously with reference to Fig. 11 are combined at a combiner 1220 in order to provide a load-shared or protected system. Each source maintains a map of its own locked optical carriers and the two output switches 1110_A, 1110_B are driven with complimentary connection maps, arrived at by negotiation between the two sources 1210_A, 1210_B.

A first non-limiting example of a suitable negotiation algorithm is one in which both units prepare an inventory of working, locked optical carriers. The source which is used to output each successive optical carrier is then chosen alternately between source 1210_A and unit 1210_B until a optical carrier is reached which is not locked by the chosen source. In that case, the optical carrier is chosen from the other source and the process is continued alternately. In a second non-limiting example of a suitable negotiation algorithm, source 1210_A could be designated the master unit and source 1210_B the

protection unit, with changeover occurring only on those wavelengths which are not locked by source 1210_A.

It is noted that in the above embodiments, the WDM device
5 222 and the WDD devices 228, 428, 628 may themselves
exhibit a temperature-dependent drift on the order of 1.3
GHz per degree Celsius (°C). Accordingly, it is within
the scope of the present invention to maintain these
10 devices at a constant temperature by a thermostatically
controlled heater, which can readily control the
temperature of the sub-mount of each device to within
0.3-1 °C.

This thermal sensitivity of the WDD devices 228, 428, 628
15 can also be used to advantage, by locking the output of
the multi-carrier optical signal source to a reference
wavelength. Specifically, whereas in previous cases, the
system frequencies F^*_i were part of a pre-determined grid
(such as the ITU grid), it is also possible to receive a
20 single reference optical frequency F_R along an optical
control channel. The goal is for the reference optical
frequency F_R to appear at the center of the main lobe
corresponding to the K^{th} optical channel output by the
WDD device 228.

25 To this end, the output of comparator H_K is used to
adjust not the reference optical frequency but rather is
used to thermally move the WDD device 228 to optimally
align the center of its K^{th} lobe with the reference
30 optical frequency F_R . This is especially practical when
the lobe-to-lobe spacing is consistent between adjacent
channels. Advantageously, this allows an absolute

frequency plan to be achieved, not just a relative frequency plan, thereby improving the precision of alignment between diverse nodes in the network.

- 5 An eighth embodiment of the invention, shown in Fig. 13, provides for insertion of a modulation signal after generation of the single-carrier optical signals by the lasers L_i but prior to demultiplexing by the WDD device 228. For example, it is within the scope of the present
- 10 invention to introduce a plurality of splitters 1310, each of which is connected between a respective one of the lasers L_i and the WDM device 222. Each splitter 1310 may suitably divert between 5 and 10 % of the optical power of the respective single-carrier optical signal
- 15 towards a respective modulator 1320, while feeding the rest of the power to the core network 226 via the WDM device 222. Of course, those skilled in the art will appreciate that other power splitting ratios are possible.
- 20
- Each modulator 1320 applies a modulation signal, suitably a tone at tone frequency T_i , to each corresponding single-carrier optical signal. To this end, the modulators 1320 may be suitably embodied as variable
- 25 optical attenuators (VOAs) based on thermo-optic effects. The outputs of the modulators 1320 are connected to respective inputs of a combiner 1330. The combiner 1330 multiplexes the individual optical signals into a multi-carrier optical signal provided to the input of the WDD
- 30 device 228.

With this configuration, which may be used with any of the above described embodiments of the invention, the optical signals being transmitted to the core network 226 are free of modulation signals (tones) because such tones
5 are introduced after the signals have been diverted to the core network 226. As a result, large amplitudes for the modulation signals are permitted as there is no associated contamination of the optical carrier signals emitted by the lasers L_i . Larger amplitudes are useful
10 as they provide additional robustness and reliability to the measurements made by the comparators H_i and reduce the required sensitivity of the tone detector.

Those skilled in the art will also appreciate that in
15 alternative embodiments of the present invention, the amplitude control loop may be dispensed with in favour of equipping each laser with a known prior art back facet monitor diode and power control loop, while retaining only the frequency control loop. Although this would
20 increase the number of optical components, due to the inclusion, in an N-channel system, of N back facet monitor diodes and independent power control loops, such an implementation is nonetheless within the scope of the present invention. In this way, amplitude equalization
25 of individual optical carriers across the optical frequency spectrum is not provided, although each carrier frequency F_i will be precisely maintained within a close range of its corresponding system frequency F^*_i , as long as the amplitude of the optical carrier is sufficiently
30 high.

It should also be understood that although the above embodiments all describe the measured amplitude offset as relying on measurements taken from channels adjacent to the channel in which the optical carrier is expected to lie, it is nevertheless within the scope of the invention to use measurements taken from channels that are even further removed. This may be especially beneficial in situations where the side lobes of an individual channel response demonstrate a significant peak at more distant intervals from the corresponding channel center frequency.

Those skilled in the art should further appreciate that the present invention is not limited to the use of tones as the modulation signals. Thus, use of the expressions "tone frequency" and "tone" herein above has been by way of example only and is merely intended to emphasize the distinction between the electrical characteristics of the modulation signals and the optical characteristics of the signals output by the lasers. Other embodiments may be contemplated in which the modulation signal may have a characteristic that allows it to be isolated and its amplitude measured in the presence of other modulation signals. Examples include signals with unique combinations of tones or with unique but constant modulation depths or even signals with unique phases or digital codes.

Moreover, those skilled in the art should also be appreciative of the fact that embodiments of the invention exist in which the use of modulated signals is not required. For example, if the lasers were quasi-

stable under open loop conditions (i.e., F_i^{open} is always in the neighbourhood of F_i^*), then the frequency control loop could operate under received d.c. power measurements at all times, thereby allowing the elimination of the modulation signals altogether, with the consequent removal of any tone-related impairments on the output optical carriers.

For example, Fig. 14 shows a ninth embodiment of the present invention which is especially suited to already partially stabilized lasers L_i , operating to within about 5-10 GHz of the system frequencies F_i^* . An example of a laser operating in this manner is a Fabry-Perot laser associated with a fiber grating to establish the tuning point. Such a part can be tuned about 10-12 GHz over a temperature range of 50 degrees Celsius and can be produced with about 5-10 GHz initial tuning accuracy.

Each of the lasers L_i outputs a single-carrier optical signal which is fed to broad-lobed WDM device 222, which combines the N single-carrier optical signals into a multi-carrier optical signal. The output of the WDM device 222 is connected, via splitter 224, both to the core network 226 and to the WDD device 628. The splitter 224 may suitably divert between 5 and 10 % of the optical power of the multi-carrier optical signal towards the WDD device 628, while feeding the rest of the power to the core network 226. Of course, those skilled in the art will appreciate that other power splitting ratios are possible, as are other output-multiplexed (or non output-multiplexed) structures.

The wavelength division demultiplexing (WDD) device 628 has been previously described with reference to Fig. 6. The WDD device 628 has $2N$ output ports P_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$. Specifically, each port is associated with
5 an optical channel having an optical pass band centered about a unique channel center frequency $F_{ch,2i+k}$. In the specific embodiment of Fig. 14, the channel center frequencies $F_{ch,2i+k}$ correspond to $F^*_i + ((-1)^k \cdot 25)$ GHz. In other words, system frequency F^*_i falls mid-way
10 between channel center frequency $F_{ch,2i-1}$ and channel center frequency $F_{ch,2i}$.

Each output port P_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, of the WDD device 628 is connected to a respective low-bandwidth
15 optical receiver R_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, which is adapted to provide opto-electronic conversion functionality. Each of the optical receivers R_{2i+k} outputs a low-bandwidth electrical version of the portion of the multi-carrier optical signal centered about the
20 corresponding channel center frequency $F_{ch,2i+k}$ which, in the embodiment of Fig. 14, corresponds to system frequency F^*_i adjusted by $(-1)^k \cdot 25$ GHz. That is to say, each optical receiver R_{2i+k} admits a low-bandwidth electrical version of the portion of the multi-carrier
25 optical signal centered about $F^*_i + (-1)^k \cdot 25$ GHz.

Each of the optical receivers R_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$, is connected to a respective power monitor 860_{2i+k} , $1 \leq i \leq N$, $-1 \leq k \leq 0$. Power monitor 860_{2i+k} is adapted to
30 measure the power in the signal admitted by the respective receiver. The outputs of power monitors 860_{2i-1} , 860_{2i} are connected to two inputs of a

comparator H_i and to two inputs of a power combiner 450_i . Thus, it is as if the switch 870_i of Fig. 8 always operated in the second state. In other words, comparator H_i evaluates the difference between the power of the optical signal in the channels centered about frequencies $F_{ch,2i-1}$ and $F_{ch,2i}$, while power combiner 450_i combines the amplitude measured by power monitor 860_{2i-1} and power monitor 860_{2i} .

10 The output of each comparator H_i , $1 \leq i \leq N$, is the previously described measured amplitude offset AO_i , which is fed to laser controller C_i associated with optical carrier i . Also, the output of power combiner 450_i is a used as the previously described measured carrier
15 amplitude AV_i which is fed to laser controller C_i associated with optical carrier i . Because tones are not used, the accuracy of the frequency control loop will depend on the tolerance of the WDM device 222, as well as on the precision, sensitivity and balance of the
20 comparators H_i .

Those skilled in the art should appreciate that in some embodiments of the invention, all or part of the functionality previously described herein with respect to
25 components such as the tone detectors D_i , comparators H_i , controllers C_i , out-of-range detectors 880_i , tone detection unit 940 and controller units 950, 1150, may be implemented as pre-programmed hardware or firmware elements (e.g., application specific integrated circuits
30 (ASICs), electrically erasable programmable read-only memories (EEPROMs), etc.), or other related components.

In other embodiments of the invention, all or part of the functionality previously described herein with respect to the tone detectors D_i , comparators H_i , controllers C_i and out-of-range detectors 880_i may be implemented as software consisting of a series of instructions for execution by a computer system. The series of instructions could be stored on a medium which is fixed, tangible and readable directly by the computer system, (e.g., removable diskette, CD-ROM, ROM, or fixed disk), or the instructions could be stored remotely but transmittable to the computer system via a modem or other interface device (e.g., a communications adapter) connected to a network over a transmission medium. The transmission medium may be either a tangible medium (e.g., optical or analog communications lines) or a medium implemented using wireless techniques (e.g., microwave, infrared or other transmission schemes).

Those skilled in the art should further appreciate that the series of instructions may be written in a number of programming languages for use with many computer architectures or operating systems. For example, some embodiments may be implemented in a procedural programming language (e.g., "C") or an object oriented programming language (e.g., "C++" or "JAVA").

While specific embodiments of the present invention have been described and illustrated, it will be apparent to those skilled in the art that numerous modifications and variations can be made without departing from the scope of the invention as defined in the appended claims.